



Features & Applications:

-  5-in-1 combo antenna
-  2xMiMo 5G-FR1 (4G compatible)
-  2xMiMo WiFi 6E/7
-  Active GNSS L1 RHCP Patch antenna
-  High out of band rejection filters
-  Adhesive mount, ideal for plastic and glass surface installation
-  Optional plastic bracket included

ELECTRICAL SPECIFICATIONS					
General Specifications – 5G FR1 / WiFi 6E/7					
Antenna type	Impedance	Polarization	Rad. Pattern	Power withstanding	DC Ground
Monopole ¹	50Ω	Vertical / Linear	Omni	2W	No
5G FR1 Antennas: 617 – 7125MHz					
Port	Frequency (MHz)	617-960	1710-2700	3300-7125	
Port 1, 2	VSWR	2.5:1	2:1	2:1	
	Avg. Peak Gain (dBi)	2.5	5.5	5.1	
	Avg. Efficiency (%)	48	62	60	
Isolation ²	Port 1-2 (dB)	10	20	30	
WiFi 6E/7 Antennas: 2400-2500 /5150-7125MHz					
Port	Frequency (MHz)	2400-2500	5150-7125		
Port 3, 4	VSWR	2:1	2:1		
	Avg. Peak Gain (dBi)	4.5	3.3		
	Avg. Efficiency (%)	60	58		
Isolation ²	Port 3-4 (dB)	13	25		
GNSS Antenna:1560-1610MHz					
Antenna type		Nominal Impedance		Polarization	
Patch antenna		50 Ω		RHCP	
Frequency (MHz)		1561.098 ± 2.046/ 1575.42 ± 1.023/ 1602.5625 ± 4			
Return Loss (dB)		<-7 dB			
LNA Gain		30dB ± 2 dB			
Current consumption		<10 mA			
DC voltage in via GNSS RF cable		3.3-5 Vdc ± 0.5V			
MECHANICAL SPECIFICATIONS					
CDB52211AM					
Dimension (L x W x H)	Weight	Color	Fixing System	Housing Material	
178 x 60x19 mm (7.01” x2.36”x 0.75”)	600 g	Black	Adhesive Mount (3M VHB 4991(Gray)) / Bracket	PC (UV-stabilized)	
Wireless Technology	No. of Port	Cable Length	Cable Type	Connector Type	
5G FR1/LTE	2	10FT (3.048M)	LMR195	SMA Male	
GNSS	1	10FT (3.048M)	LMR100	SMA Male	
WiFi 6E/7	2	10FT (3.048M)	LMR195	RP SMA Male	
ENVIRONMENTAL SPECIFICATIONS					
CDB52211AM					
Storage Temperature	Operating Temperature	Ingress Protection		RoHS Compliant	
-40 / +85° C	-40 / +85° C	IP65		Yes	


Notes:

1. 5G-FR1 and WiFi 6E/7: Multi-Band Monopoles with built in ground plane, 2. Minimum Isolation (dB)


Mechanical Drawing

CDB52211AM


Antenna



3M VHB Tape



Plastic Bracket



*Tape and bracket package separately


Unit: mm/ inches

Charts

 Test data
 5G NR Antennas


VSWR vs Frequency

Measured in PSU 20230510




VSWR vs Frequency

Measured in PSU 20230510



Isolation vs Frequency

Measured at PSU 20230510




*Antenna VSWR test in free space and 10-ft cables

Charts

Test data
5G NR Antennas


Efficiency vs Frequency

Measured at PSU 20230510



Efficiency vs Frequency



Measured at PSU 20230525



* antenna test in free space and 1-ft cables

Charts


Test data
5G NR Antennas




* Antenna test in free space and 1-ft cables

Charts

Test data
GNSS Antenna




LNA Gain and out-of-band rejection







Testing Setup

CDB52211AM




Radiation Pattern

Test data
5G NR-1 Antennas




Radiation Pattern

Test data
5G NR-1 Antennas




Radiation Pattern


Test data
5G NR-2 Antennas




Radiation Pattern

Test data
5G NR-2 Antennas


Radiation Pattern

Test data
WiFi1-Antennas

Radiation Pattern

Test data
WIFI-1 Antennas


Radiation Pattern


Test data
WiFi2-Antennas


Candy Bar 5G-NR / GNSS / WiFi 6E/7 Vehicular Multiband Antenna

CDB52211AM, 617-7125 / 1560-1610MHz / 2400-7125MHz

Radiation Pattern


Test data
WIFI-2 Antennas



Packing

CDB52211AM

1.Put the accessories: the bracket, the tape, and the screw into one PE bag.



2.Put one antenna and one bag accessories into a big packing bag.



3. Put the partition board into the outer box, and put 1 products in every grid, 6 sets products per outer box.




Mounting Instructions

CDB52211AM


Option 1: Tape Mount

Apply to the surface of the glass fiber or plastic material, the antenna could be adhered on the surface by the 3MVHB adhesive tape (3M VHB4959 80X50mm).



Option 2: Plastic Bracket Mount

Firstly, fix the bracket on the customer side with 4sets M4 screws, M4 nut, flat washer and spring washer;
Then push the antenna into the plastic bracket.



For More Information:

Americas - antennas.us@pulseelectronics.com | Europe - antennas.eu@pulseelectronics.com | Asia - antennas.as@pulseelectronics.com | Questions? +1-800-ANTENNA
Performance warranty of products offered on this data sheet is limited to the parameters specified. Data is subject to change without notice. Other brand and product names mentioned herein may be trademarks or registered trademarks of their respective owners. © Copyright , 2020. Pulse Electronics, Inc. All rights reserved.
Company address: Pulse Electronics, a YAGEO Company, 15255 Innovation Drive, Suite #100, San Diego, CA 92128

'YAGEO Corporation and its affiliates do not recommend the use of commercial, automotive, and/or COTS grade products for high reliability applications or manned space flight.'